MC34063A Boost Converter Module

FEATURES

- MC34063A Boost Converter Module
- Input Voltage: 3.3V
- Output Voltage: 5.0V
- Output Current: Max. 175mA
- Compact Size Step-Up Converter



APPLICATIONS

- Simple Converter from 3.3V to 5V with 175mA

ORDERING INFORMATION

Part Number	MBS34063-01
Device	MC34063A Boost Converter Module
Package	Assembled Module (31mm X 25mm)

DESCRIPTION

The MC34063A Boost Converter Module receives 3.3V input voltage and converts it into a stable 5V DC output voltage.

APPLICATION GUIDE

The MC34063A Boost Converter Module is capable of delivering around 175mA maximum output current, which is suitable for most small electronic projects. Compact and inexpensive, this board is perfect for use when a 3.3V to 5V power source conversion is needed.

MC34063A Boost Converter Module

SCHEMATICS



LAYOUT

Top



Bottom



MC34063A Boost Converter Module

SIZE INFORMATION



PRODUCT IMAGE





I/O PORT CONFIGURATION AND DESCRIPTION



Designator	Port Name	Port Description
1	Input Connector	3.3V Input Connector
2	Output Connector	5.0V Output Connector

REVISION NOTICE

The description in this datasheet is subject to change without any notice to describe its electrical characteristics properly.

DC-DC Converter Control Circuits MC34063AG

FEATURES

- Output Switch Current In Excess of 1.5A
- 2% Reference Accuracy
- Low Quiescent Current : 2.5mA(Typ.)
- Operating From 3V to 40V
- Frequency Operation to 100KHz
- Active Current Limiting
- MC34063AG is Halogen Free Products



SOP-8



DIP-8

APPLICATION

- Battery Chargers
- NICs / Switches / Hubs
- ADSL Modems
- Negative Voltage Power Supplies

ORDERING INFORMATION

Device	Package
MC34063AGD	SOP-8
MC34063AGN	DIP-8

DESCRIPTION

The MC34063AG series is a monolithic control circuit delivering the main functions for DC-DC voltage converting. The device contains an internal temperature compensated reference, comparator, duty cycle controlled oscillator with an active current limit circuit driver and high current output switch.
Output voltage is adjustable through two external resistors with a 2% reference accuracy.
Employing a minimum number of external components the MC34063AG devices series is designed for Step-Down, Step-Up and Voltage-Inverting applications.

ABSOLUTE MAXIMUM RATINGS (Note 1)

CHARACTERISTIC	SYMBOL	MIN.	MAX.	UNIT
Power Supply Voltage	V_{CC}	-	40	V
Comparator Input Voltage Range	V_{IR}	-0.3	40	V
Switch Collector Voltage	V_{SWC}		40	V
Switch Emitter Voltage(V_{SWC}=40V)	V_{SWE}		40	V
Switch Collector to Emitter Voltage	V_{CE}		40	V
Driver Collector Voltage	V_{dc}	-	40	V
Driver Collector Current (Note 2)	I_{dc}	-	100	mA
Switch Current	I_{SW}	-	1.5	A

ABSOLUTE MAXIMUM RATINGS (Continued)

CHARACTERISTIC	SYMBOL	MIN.	MAX.	UNIT
Junction Temperature Range	T_J	-40	150	°C
Storage Temperature Range	T_{STG}	-65	150	°C

Note 1. Absolute Maximum Ratings are those values beyond which damage to the device may occur. Functional operation under these conditions is not implied.

(*) This value depends from thermal design of PCB on which the device is mounted.

RECOMMENDED OPERATING CONDITIONS

CHARACTERISTIC	SYMBOL	MIN.	MAX.	UNIT
Supply Voltage	V_{CC}	3	40	V
Operating Junction Temperature	T_J	-40	125	°C
Operating Ambient Temperature	T_A	-40	125	°C

ORDERING INFORMATION

Package	Order No.	Description	Supplied As	Status
SOP-8	MC34063AGD	1.5A, 100kHz	Tape & Reel	Active
DIP-8	MC34063AGN	1.5A, 100kHz	Tube	Active

PIN CONFIGURATION



SOP-8 / DIP-8

PIN DESCRIPTION

Pin No.	DIP-8 PKG	
	Name	Function
1	Switch Collector	Internal switch transistor collector
2	Switch Emitter	Internal switch transistor emitter
3	Timing Capacitor	Timing Capacitor to control the switching frequency
4	GND	Ground pin for all internal circuits
5	Comparator Inverting Input	Inverting input pin for internal comparator
6	V_{CC}	Voltage supply
7	I_{PK} Sense	Peak Current Sense Input by monitoring the voltage drop across an external I sense resistor to limit the peak current through the switch
8	Driver Collector	Voltage driver collector

BLOCK DIAGRAM



ELECTRICAL CHARACTERISTICS

(Refer to the test circuits, V_{CC}=5V, T_A=T_{LOW} to T_{HIGH}, unless otherwise specified, see note 2)

SYMBOL	PARAMETER	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT
OSCILLATOR						
F_{OSC}	Frequency	V_{PIN5}=0V, C_T=1nF, T_A=25℃	24	33	42	KHz
I_{CHG}	Charge Current	V_{CC}=5 to 40V, T_A=25℃	24	35	42	μA
I_{DISCHG}	Discharge Current	V_{CC}=5 to 40V, T_A=25℃	140	220	260	μA
I_{DISCHG}/I_{CHG}	Discharge to Charge Current Ratio	Pin 7= V_{CC}, T_A=25℃	5.2	6.5	7.5	
$V_{IPK(SENSE)}$	Current Limit Sense Voltage	I_{CHG}=I_{DISCHG}, T_A=25℃	250	300	350	mV
OUTPUT SWITCH						
$V_{CE(SAT)}$	Saturation Voltage, Darlington connection	I_{SW}=1A, Pins 1,8 connected		1.0	1.3	V
$V_{CE(SAT)}$	Saturation Voltage	I_{SW}=1A, R_{PIN8}=82Ω to V_{CC}, Forced β ~ 20		0.45	0.7	V
h_{FE}	DC Current Gain	I_{SW}=1A, V_{CE}=5V, T_A=25℃	50	75		
$I_{C(OFF)}$	Collector Off-State Current	V_{CE}= 40V		1.0	100	μA
COMPARATOR						
V_{TH}	Threshold Voltage	T_A=25℃	1.225	1.25	1.275	V
		T_A=T_{LOW} to T_{HIGH}	1.21		1.29	V
REG_{LINE}	Threshold Voltage Line Regulation	V_{CC}= 3 to 40V		1.4	5	mV
I_{IB}	Input Bias Current	V_{IN}= 0V		-20	-400	nA
TOTAL DEVICE						
I_{CC}	Supply Current	V_{CC}= 5 to 40V, C_T=1nF Pin7= V_{CC}, V_{PIN5}>V_{TH}, Pin2=GND Remaining pins open		1.4	4	mA

Note 1. Maximum package power dissipation limit must be observed.

Note 2. T_{LOW}= '-40℃, T_{HIGH}= '+125℃

Note 3. If Darlington configuration is not used, care must be taken to avoid deep saturation of output switch.
The resulting switch-off time may be adversely affected.
In a Darlington configuration the following output driver condition is suggested:

Forced β of output switch : $\frac{I_{C(OUTPUT)}}{I_{C(DRIVER)} - 7.0mA^{*}} \geq 10$

* Currentless due to a built in 1KΩ anti-leakage resistor

TYPICAL ELECTRICAL CHARACTERISTICS

Emitter Follower Configuration Output Saturation Voltage vs. Emitter Current



Output Switch ON-OFF Time vs. Oscillator Timing Capacitor



Common Emitter Configuration Output Switch Saturation Voltage vs. Collector Current



Current Limit Sense Voltage (V_{IPK}) vs. Temperature



Standby supply current vs. Supply voltage



TYPICAL APPLICATION CIRCUIT

Step-Up Converter



Step-Down Converter



Step-Up with External NPN Switch



Voltage Inverting Converter



Step-Down with External PNP Switch



Voltage Inverting with External NPN Switch



DESIGN FORMULA TABLE

CALCULATION	STEP-UP	STEP-DOWN	VOLTAGE-INVERTING
t_{on} / t_{off}	$\frac{Vout + VF - Vin(min)}{Vin(min) - Vsat}$	$\frac{Vout + VF}{Vin(min) - Vsat - Vout}$	$\frac{\lvert Vout\rvert + VF}{Vin + Vsat}$
$(t_{on}+ t_{off})max$	$\frac{1}{fmin}$	$\frac{1}{fmin}$	$\frac{1}{fmin}$
C_T	$4.0 \times 10^{-5} \times ton$	$4.0 \times 10^{-5} \times ton$	$4.0 \times 10^{-5} \times ton$
$I_{pk(switch)}$	$2 \times Iout(max) \times (\frac{ton}{toff} + 1)$	$2 \times Iout(max)$	$2 \times Iout(max) \times (\frac{ton}{toff} + 1)$
R_{SC}	$\frac{0.3}{Ipk(Switch)}$	$\frac{0.3}{Ipk(Switch)}$	$\frac{0.3}{Ipk(Switch)}$
$L_{(min)}$	$(\frac{Vin(min) - Vsat}{Ipk(Switch)}) \times ton(max)$	$(\frac{Vin(min) - Vsat}{Ipk(Switch)}) \times ton(max)$	$(\frac{Vin(min) - Vsat}{Ipk(Switch)}) \times ton(max)$
C_O	$9 \times \frac{Iout \times ton}{Vripple(pp)}$	$\frac{Ipk(switch) \times (ton + toff)}{8 \times Vripple(pp)}$	$9 \times \frac{Iout \times ton}{Vripple(pp)}$

V_{SAT} - Saturation voltage of the output switch.
V_F - Forward voltage drop of the output rectifier.
V_{in} - Nominal input voltage.
V_{out} - Desired output voltage, V_{out} = 1.25(1+R2/R1)
f_{min} - Minimum desired output switching frequency at the selected values of V_{in} and I_{out}.
$V_{ripple(p-p)}$ - Desired peak-to-peak output ripple voltage. In practice, the calculated capacitor value will need to be increased due to its equivalent series resistance and board layout. The ripple voltage should be kept to a low value since it will directly affect the line and load regulation.

REVISION NOTICE

The description in this datasheet can be revised without any notice to describe its electrical characteristic properly.